



Zero Bias Schottky Detector

The content of this specification may change without notification 12/01/2009



Zero Bias Schottky Detector

P/N: JXWBJBQ-0120-PZ

| | |
|---------------------------|----------|
| Frequency Range(GHz) | 0.1-2 |
| Sensitivity[K](mV/mW) | 500 min |
| Flatness vs Frequency(dB) | ±0.3 |
| TSS(dBm) | -52 |
| Video Capacitance(pf) | 270 |
| Output Power(mW) | 100 max |
| Output | Positive |
| Connector | SMA |

Outline Drawing (Size: mm)

